

## 4x 30A ESC, 2A BEC



**Produktkode:** 516  
**Tilgjengelighet:** 6

**Pris:** kr. 210,00

### Short Description

4pcs HP30A Brushless speed controller ESC MultiCopter KK Quad-rotor X-copter

### Beskrivelse

Description:

4X 30A Brushless speed controller ESC MultiCopter KK Multi-Copter Quad X-flying

Compatible with: 400-450 helicopters / Aircraft or Quad-Rotor Multi RC Heli

### HOBBYPOWER 30A

Program same with Hobbywing 30A

4 sets good for quad-rotor KK multi-copter  
quantity:4 sets

### Specification

1.1 Output: Continuous 30A, Burst 40A up to 10 Secs.

1.2 Input Voltage: 2-3 cells lithium battery or 5-8 cells NiCd/NIMh battery.

1.3 BEC: 2A / 5V (Linear mode).

1.4 Max Speed: 210,000rpm for 2 Poles BLM, 70,000rpm for 6 poles BLM, 35,000rpm for 12 poles BLM.

(BLM: BrushLess Motor)

1.5 Size: 45mm (L) \* 24mm (W) \* 10mm (H).

1.6 Weight: 25g.

## 2 Features

2.1 Safety Arming Feature: Regardless the throttle stick position, the motor will not spin after battery connected.

2.2 Throttle Calibration: Throttle range can be configured to provide best throttle linearity, fully compatible with all market available transmitters.

2.3 Programmable Items:

Brake Setting: brake enabled / brake disabled.

Battery Type: Li-xx(Li-ion or LiPo) / Ni-xx(NiMh or NiCd).

Low Voltage Protection Mode(Cutoff Mode): Gradually reduce the output power / Cutoff the output power.

Low Voltage Cutoff Protection Threshold (Cutoff Threshold): low / medium / high.

Start Mode: normal / soft / very soft.

Timing: low / medium / high.

Reset: reset all the programmable items to their default settings.

2.4 Full Protection Features: Low voltage cutoff protection / Over-heat protection / Throttle signal lost protection.

Package Includes: (as shown in the picture)

4pcs HP30A HOBBYPOWER 30A Build-in BEC 2A Brushless ESC